



Assignment of the DC-Servo Controllers to the Motors of the GM55 - GM110 Series

Motortyp Motortype Motortype	Nennspannung Rated voltage Tension nominale	Nennstrom Rated current Courant nominale	Spitzenstrom Peak current Courant maxi	DC- Servoregler DC- Servo controller Amplificateur de puissance
GM55K	30 VDC	3,7 A	11,1 A	Kern Drive 60 8/16
GM55M	30 VDC	4,5 A	13,5 A	Kern Drive 60 8/16
GM55L	48 VDC	3,6 A	10,8 A	Kern Drive 60 8/16
GM68K	48 VDC	3,0 A	9,0 A	Kern Drive 60 4/8
GM68M	48 VDC	4,3 A	12,9 A	Kern Drive 60 8/16
GM68L	48 VDC	5,4 A	16,2 A	Kern Drive 60 8/16
GM82K	50 VDC	4,0 A	12,0 A	Kern Drive 60 8/16
GM82M	50 VDC	5,8 A	17,4 A	Kern Drive 60 8/16
GM82L	50 VDC	6,5 A	19,5 A	Kern Drive 60 14/28
GM92M	50 VDC	9,8 A	29,4 A	Kern Drive 60 14/28
GM92L	50 VDC	10,0 A	30,0 A	Kern Drive 60 14/28
GM110K	120 VDC	5,4 A	16,2 A	Kern Drive 200 14/28
GM110L	48 VDC	14,0 A	42,0 A	Kern Drive 60 14/28